



Connection via CT for single and three-phase network, 3 or 4-wires.
Phase sequence correction, diagnostic.
Can be accessorised with up to 4 additional modules.

Functions

- Phase and linked voltage
- Min. and max. phase voltage
- THDV
- Voltage Harmonic analysis
- Voltage crest factor
- Phase angle between voltage
- Neutral and phase current
- Current demand and current max. demand
- Average current
- THDI
- Current Harmonic analysis
- Current crest factor
- Phase angle between current
- Active, reactive phase power
- Power demand and power max. demand
- Positive and negative active and reactive energy
- Power factor
- Phase angle between current and voltage
- Frequency
- Run hour meter, count start with voltage or power present

Cat. Nos.	Nemo 96HD+			
	Input (A)	Input* (V)	Auxiliary supply	Output
MF96021A	1 + 5	80...690	80...265Vac 100...300Vdc	up 4 additional modules
MF96022A	1 + 5	80...690	16...60Vdc	up 4 additional modules

* Three-phase input 80...690, Single -phase input 230V

Cat. Nos.	Additional modules
	Descriptions
IF96001	Module RS485 Modbus RTU/TCP
IF96012	Module RS485 Modbus RTU/TCP + memory
IF96002	Module RS232 Modbus RTU/TCP
IF96007A	Module Profibus EN50170 - DP0
IF96009	Module LonWorks
IF96013	Module M-Bus EN1434-3
IF96014	Module RS485 BACnet MS-TP
IF96015	Module Ethernet
IF96003	Module with 2 energy pulse outputs (SPST)
IF96004	Module with 2 x 0/4..20mA analogue outputs
IF96005	Module with 2 alarm relay outputs (SPST)
IF96006	Neutral current measurement from CT /1A or 5A programmable
IF96016	Module temperature measurement 2 inputs from PT100
IF96010	Module with 2 input SPST-NO 2 relay outputs SPST-NO
IF96011	Module with 2 input 12/24Vcc 2 relay outputs SPST-NO

Technical features

TECHNICAL NOTES	NT904
INPUT	
Three-phase voltage (V)	80...690 (phase-phase)
Single-phase voltage (V)	50...400V
Current rating	1A - 5A
External CT ratio	max 50kA/5A - max 10kA/1A
External VT ratio	primary voltage max 150kV
Continuous overload	1,2In
Istantaneous overload	20Imax/0,5s
Reference frequency	50Hz
Frequency tolerance	45...63Hz
Type of measurement	true RMS
Voltage rated burden (VA)	≤ 0,1VA (phase-neutral)
Current rated burden (VA)	≤ 0,2VA (for phase)

AUXILIARY SUPPLY	
Rated value Uaux	80...265Vac
Reference frequency	50
Frequency tolerance	45...63Hz
Rated burden	≤ 2,5VA (230Vac backlight 30% without external modules)
Rated value Uaux	100...300Vdc 11...60Vdc
Rated burden	≤ 3,5W (without modules)

ACCURACY	
CONFORMITY ACCURACY WITH EN/IEC 61557-12	<ul style="list-style-type: none"> - voltage: cl.0,5 - Current: cl. 0,5 - Active energy: cl.0,5 - Reactive energy cl.2 - Active power cl.0,5 - Reactive power cl.1 - Apparent power cl.1 - Frequency cl.0,5 - Power factor cl.0,5 - THD cl.2

DISPLAY	
Type of display	LCD backlighted
Digit height	8/12mm
Energy resolution	depending on the CT/VT ratio**

MECHANICAL FEATURES	
Housing	flush mounting (panel cutout 92x92mm)
Front frame	96x96mm
Housing material	self-extinguishing polycarbonate
Protection degree	IP20 terminals/ IP54 front frame
Connections type	screw terminals
Rigid cable	max 4,5mm ²
Flexible cable	max 2,5mm ²


ENVIRONMENTAL CONDITIONS	
Nominal temperature range	-5...55°C
Limit range for storage and transport	-25...70°C
Suitable for tropical climates	yes
Max.power dissipation*	≤5W

* for switchboard thermal calculation


** kCT*kVT	MAXIMUM DISPLAY
1...9	999999,99kWh/kvarh
10...99	9999999,9kWh/kvarh
100...999	99999999kWh/kvarh
1000...9999	999999,99MWh/Mvarh
10000...99999	9999999,9MWh/Mvarh
100000...400000	99999999MWh/Mvarh

Output

ADDITIONAL MODULES	
N. max installable module	4
Installation position	A-B-C-D




Dimensions




Wiring diagrams



Single phase network




3-phase network, 3 wire




3-phase network, 3 wire, 1 System





3-phase network, 4 wire, 1 System



3-phase network, 4 wire



3-phase network, 4 wire (ARON L1-L3)



Whilst every effort has been made to ensure the accuracy of this specification, we cannot accept responsibility for damage, injury, loss or expense from errors or omissions. In the interest of technical improvement, this specification may be altered without notice.

For pricing or any further information, please contact Omni Instruments Ltd.